

COMMUNICATIONS RECEIVER
VR-120D

Wideband Coverage: 0.1~1299.995* MHz FM/WFM/AM

Rugged Professional Communications Receiver

- Professional Grade Receiver
- Wide Frequency Coverage
- 640 Memory Channels
- Durable and Reliable for Outdoor Use
- Fully-illuminated Keypad and Display
- Four-Button Simple Operation
- Long Battery Life
- Multiple Power Source Capability

NEW EXTERNAL DC INPUT

Use either the PA-30B/C/U AC Adapter or E-DC-15 DC Cable to power your VR-120D.



OPTIONAL CHARGING STAND

Use the NC-82* Charger Stand and CA-34* Charger Sleeve to charge the optional FNB-79* Ni-Cd Battery Pack, using the PA-30* AC Adapter.

*Optional accessories

Actual Size

YAESU
Choice of the World's top DX'ersSM

RUGGED OUTDOOR-READY CASE CONSTRUCTION!

To survive the rigors of outdoor use, the VR-120D is housed in a durable, high-impact polycarbonate case, and it is protected against water ingress per JIS II specifications.

ULTRA-LONG BATTERY LIFE AND EXT.DC INPUT

When you're out in the field, and can't afford to miss out on weather information, long battery life in your receiver is essential. The VR-120D, especially designed for low current consumption, can provide up to 20 hours of operation on a pair of "AA" alkaline cells (at 40 mW audio output), and the Battery Saver feature cuts battery consumption dramatically when no signals are being received. An icon on the LCD indicates when the batteries are getting low, alerting you to the need to replace them.

New Charging System for Optional Ni-Cd Battery



BNC-TYPE ANTENNA CONNECTOR

For ease of making connections, and for maximum compatibility with after-market antennas, the VR-120D's top panel is equipped with a handy BNC-type antenna connector.



*Internal "Bar" Antenna for AM BC

STRAIGHTFORWARD 4-BUTTON OPERATION

The no-nonsense front panel of the VR-120D contains four large keys which are used for command of the receiver's many operating functions. These keys, the "Function" key on the side, and the Main Tuning Knob are all you need to tune in on the DX action! The display and function keys are fully illuminated, for ease of operation at night.



WIDEBAND FREQUENCY COVERAGE WITH EASY ACCESS!

The VR-120D provides continuous coverage of the frequency range 0.1~1299.995 MHz (cellular frequencies are blocked and non-restorable). When you set a frequency, the operating mode (AM/FM/Wide-FM) and channel steps appropriate for that frequency range are automatically selected, for ease in tuning around in search of other stations. Of course, you can manually select the mode and tuning steps, if you have other requirements in that tuning range.

About this brochure: we have made this brochure as comprehensive and factual as possible. We reserve the right, however, to make changes at any time in equipment, optional accessories, specifications, model numbers, and availability. Precise frequency range may be different in some countries. Some accessories shown herein may not be available in some countries. Some information may have been updated since the time of printing; please check with your Authorized Yaesu Dealer for complete details.

The available tuning ranges are:

| BAND | FREQUENCY RANGE (MHz) | BAND | FREQUENCY RANGE (MHz) |
|-------|-----------------------|--------|-----------------------|
| BC | 0.100 ~ 7.000 | VHF-TV | 174.000 ~ 336.000* |
| SW | 7.000 ~ 50.500 | ACT-1 | 336.000 ~ 420.000* |
| HAM-1 | 50.500 ~ 54.000 | HAM-3 | 420.000 ~ 470.000 |
| FM | 54.000 ~ 108.000 | UHF-TV | 470.000 ~ 770.000* |
| AIR | 108.000 ~ 142.000 | ACT-2 | 770.000 ~ 1240.000* |
| HAM-2 | 142.000 ~ 174.000 | HAM-4 | 1240.000 ~ 1299.995 |

*Cellular / image / restricted frequencies Blocked

SPECIAL "PRESET MODE" AIDS IN QUICK TUNING!

A special bank of twelve "Preset Mode" memories is provided, giving you a starting point for tuning within the available bands. These frequencies are chosen for maximum convenience in finding the action, so you won't have far to tune when you're searching for excitement!

The Preset Mode channel frequencies are:

| CHANNEL NUMBER | PRE-PROGRAMMED FREQUENCY (MODE) | CHANNEL NUMBER | PRE-PROGRAMMED FREQUENCY (MODE) |
|----------------|---------------------------------|----------------|----------------------------------|
| 0 | 0.520 MHz (AM) | 7 | 88.000 MHz (WFM) |
| 1 | 1.800 MHz (AM) | 8 | 144.000 MHz (FM) |
| 2 | 3.600 MHz (AM) | 9 | 430.000 MHz (FM) |
| 3 | 7.000 MHz (AM) | 10 | 1240.000 MHz (FM) |
| 4 | 10.500 MHz (AM) | 11 | Weather Channels (WX-01 ~ WX-10) |
| 5 | 21.000 MHz (AM) | 12 | Recalls Memory Group 0 |
| 6 | 50.500 MHz (FM) | | |

CATCH ALL THE SHORTWAVE BROADCAST ACTION FROM AROUND THE WORLD!

You'll never have to wait for "News at Eleven" when you carry the VR-120D with you! Hear exciting shortwave broadcasts from around the world, including Voice of America, BBC, Radio Japan, Deutsche Welle, and countless others, and take advantage of the special Shortwave Broadcast 89-channel Memory Bank for quick checking of 23 popular World Band stations.

SUPER-SIMPLE ONE-TOUCH MEMORIES FOR HIGH PRIORITY STATIONS!

You can set up the VR-120D so that four high-priority stations may be recalled from special memory channels, using a single press of one of the front panel keys. The four buttons which may be utilized, and the corresponding memory channels, are:

| KEY | MEMORY CHANNEL # | KEY | MEMORY CHANNEL # |
|-----|------------------|------|------------------|
| BND | 060 | SCAN | 062 |
| V/M | 061 | MODE | 063 |

VERSATILE 640-CHANNEL MEMORY SYSTEM!

The VR-120D includes a versatile 640-channel Memory system, which allows partitioning of the channels into ten "Banks" of 64 channels each. You can group shortwave broadcast, FM broadcast, Public Safety, and Amateur Radio channels separately, for maximum tuning convenience!

WIDE SELECTION OF SCANNING MODES!

Efficient scanning is the key to any receiver's performance, and the VR-120D is a champion when it comes to scanning! A special "Search Band Scanning" function assigns seven memory channels as scanning limits, and for skipping particular frequencies a 64-channel "Skip" memory bank lets you tune past stations you don't need to monitor. Among the Memory Scan features are: ●Full Memory Scan ●Memory Bank Scan ●Selected Memory Channel ("Preferential") Scan ●Programmable Band-Limit Memory Scan (PMS) ●Smart Search™ (Automatic Memory Loading) ●Priority Channel Watch ●Dual Watch

EXPANDED FUN AND GAMES!

The VR-120D includes a "Channel Counter" feature, which measures the frequency of a very strong signal in your immediate vicinity, allowing you to zero in manually on the other station's frequency. And if you experience a lull in the monitoring action, play the VR-120D Slot Machine Game! A three-column random-number generator lets you match your wits against the VR-120D's microprocessor in an amusing game of chance.

AND MUCH, MUCH MORE. . .

- Front panel Key Lock ●Key Beeper On/Off selection
- Battery-Saving Time-Out Timer ●Front-End Attenuator for Strong-Signal Conditions ●Menu Selection of Earpiece Antenna ●S-Meter Buzzer ●Cloning Capability to other VR-120Ds

Specifications

Frequency Range: 100 kHz ~ 1299.995 MHz*
 Receiving Mode: AM/FM/WFM
 Circuit Type: Triple Conversion Super-heterodyne
 Memory Channels: 640 Channels
 Memory Banks: 10 Banks (@ 64 Channels)
 Antenna Impedance: 50-Ohm unbalanced, BNC receptacle
 Intermediate Frequencies: 248.45 MHz, 15 MHz, 450 kHz
 Sensitivity (Typical): 200 kHz ~ 5 MHz: AM 3.5 dB (1.5 V)
 5 ~ 160 MHz: AM -4.4 dB (0.6 V)
 FM -10.4 dB (0.3 V)
 WFM -1.0 dB (0.9 V)
 160 ~ 370 MHz: AM -4.4 dB (0.6 V)
 FM -10.4 dB (0.3 V)
 WFM -4.4 dB (0.6 V)
 370 ~ 520 MHz: FM -10.4 dB (0.3 V)
 WFM 0 dB (1.0 V)
 520 ~ 1300 MHz: FM -3.0 dB (0.7 V)
 WFM 9.5 dB (3.0 V)
 Selectivity: WFM 200 kHz/-6 dB
 AM/FM 16 kHz/-6 dB
 Conducted Spurious Emission: Less than -54 dBm
 Supply Voltage: 2.2 ~ 3.5 V DC; Internal Battery (Nominal: 3.0 V DC)
 5.5 ~ 10.0 V DC (EXT DC)
 Current Consumption: Approx. 95 mA (Receive, AF Output 50 mW)
 Approx. 15 mA (Standby, Saver 1.4 on)
 Approx. 55 mA (Standby, Saver off)
 Operating Temp: +14°F ~ +122°F (0°C ~ +50°C)
 AF Output: Approx. 80 mW (8% THD)
 Case Size: 3.3" X 2.3" X 1.0" WHD (85 X 59 X 26 mm) w/o knobs
 Weight: Approx. 6.9 oz. (195 g) w/battery & antenna
 *Cellular / image / restricted frequencies Blocked

Specifications are subject to change without notice.

OPTIONAL ACCESSORIES



DC Cable with Cigar-Lighter Plug E-DC-15 AC Adapter PA-30B/C/U* Ni-Cd Battery Pack FNB-79 Charger Sleeve CA-34 (Requires PA-30B/C/U*) Charger Stand NC-82 Cloning Cable CT-35 Soft Case CSC-76

YAESU VERTEX STANDARD CO., LTD.
 4-8-8 Nakameguro, Meguro-ku, Tokyo 153-8644, Japan

VERTEX STANDARD Phone 562/404-2700; Fax 562/404-1210
 Email: amateursales@vxstdusa.com

For the latest Yaesu news, visit us on the Internet:
<http://www.vxstdusa.com> <http://www.yaesu.co.uk>

US Headquarters
 17210 Edwards Road, Cerritos, CA 90703, U.S.A.
International Division
 8350 N.W. 52nd Terrace, Suite 201, Miami, FL 33166, U.S.A.

YAESU EUROPE B.V.
 P.O. Box 75525 1118 ZN, Schiphol, The Netherlands

YAESU UK LTD. Email: sales@yaesu.co.uk
 Unit 12, Sun Valley Business Park, Winnall Close
 Winchester, Hampshire, SO23 0LB, U.K.

VERTEX STANDARD HK LTD.
 Unit 5, 20/F., Seaview Centre, 139-141 Hoi Bun Road,
 Kwun Tong, Kowloon, Hong Kong